



IBS-DMAG
Creation Hall, KAIST Munji Campus



High-Temperature Superconducting (HTS) Multiple-Cell Cavities for High-Mass Axion Search

Jiwon Lee

KAIST & IBS-DMAG

※ IBS-DMAG is the successor of IBS-CAPP

Table of contents

- Introduction: Cavity Axion Haloscope
- Motivation & Key Technologies
 - Multiple-Cell Cavities
 - HTS Cavities
- Development of an HTS double-cell cavity
- Performance Test
- Toward the Axion Search
- Summary

Axion detection setup



Experimental Tests of the “Invisible” Axion

P. Sikivie

Physics Department, University of Florida, Gainesville, Florida 32611

(Received 13 July 1983)

Experiments are proposed which address the question of the existence of the “invisible” axion for the whole allowed range of the axion decay constant. These experiments exploit the coupling of the axion to the electromagnetic field, axion emission by the sun, and/or the cosmological abundance and presumed clustering of axions in the halo of our galaxy.



PACS numbers: 14.80.Gt, 11.30.Er, 95.30.Cq

Introduction

• Cavity Axion Haloscope

Proposed by Pierre Sikivie in 1983

→ The most sensitive method for detecting axion dark matter



When $f_a = f_{cav}$

→ resonant conversion

Unknown m_a

→ Resonant frequency tuning

→ Dielectric or metal rod

Resonant microwave cavity in a cryogenic environment

Motivation & Key Technologies

- Axion conversion power

$$P_{a\gamma\gamma} = g_{a\gamma\gamma}^2 \frac{\rho_a}{m_a} B^2 V C \frac{\beta}{1 + \beta} \frac{Q_l Q_a}{Q_l + Q_a}$$

- Scan rate

$$\frac{df}{dt} \propto \frac{B^4 V^2 C^2}{T_{sys}^2} Q_l Q_a$$

$Q_l \gg Q_a$ or $Q_l \ll Q_a$
Jinsu Kim, Patras (2023)

- Goal 


B^4, V^2, C^2, Q_l
→ Enhancing $\frac{df}{dt}$

$g_{a\gamma\gamma}$: Axion photon coupling
 ρ_a : Axion density in the local dark-matter halo
 B : Externally applied B-field
 V : Cavity volume
 C : Cavity form factor
 Q_l : Loaded Cavity Q-factor
 Q_a : Axion Q-factor
 β : antenna coupling coefficient
 T_{sys} : system noise temperature

1. Multiple-Cell Cavities



Maximize V
for higher f



$$Q_l \uparrow \sim \frac{1}{R_s \downarrow}$$

2. HTS Cavities

D. Kim *et al.*, Journal of Cosmology and Astroparticle Physics **2020**, (2020).

Multiple-Cell Cavities

- Goal 


$$B^4, V^2, C^2, Q_l$$

$$\rightarrow \text{Enhancing } \frac{df}{dt}$$

※ In the previous slide




- Why are Multiple-Cell Cavities needed? 

For higher frequency searches



Unavoidable **volume loss**
(Meanwhile, the fixed magnet bore radius)

(Example: 100 mm diameter, 200 mm height, 5 mm wall thickness)

Multiple cavity Array of identical cavities	Multiple-cell cavity	
 <p> $f_{TM_{010}} = 7.30 \text{ GHz}$ $V = 0.62 L$ $\frac{df}{dt} = 1.0$ 4 antenna Quad cavity </p>	 <p> $f_{TM_{010}} = 5.89 \text{ GHz}$ $V = 1.08 L$ $\frac{df}{dt} = 2.72$ 1 antenna Quad-cell cavity </p>	 <p> $f_{TM_{010}} = 7.60 \text{ GHz}$ $V = 1.02 L$ $\frac{df}{dt} = 1.98$ 1 antenna Sext-cell cavity </p>
<p>Intuitive, but... Inefficient use of volume. Complicated tuning system.</p>	<p>Minimize volume loss Use a single antenna → Simplified readout chain</p>	

Two times higher

※ For more details, please refer to Dr. Danho Ahn's materials

HTS Cavities

ω : resonant frequency
 U : energy stored in the cavity
 P_d : power dissipated in the cavity
 R_s : surface resistance

• Goal 

B^4, V^2, C^2, Q_l
→ Enhancing $\frac{df}{dt}$

※ In the previous slide

• Why are HTS cavities needed? 



Cavity quality factor: $Q = \omega \frac{U}{P_d} = \omega \frac{\frac{\mu_0}{2} \int |H|^2 dV}{\frac{R_s}{2} \oint |H|^2 dS} = \frac{G}{R_s} \propto \frac{1}{R_s} \rightarrow \text{Superconductor!}$

Magnetic fields on the **order of 10 tesla** are used at IBS-DMAG.

Most superconductors (such as Type-I, NbTi, and Nb₃Sn) cannot maintain their performance at such high magnetic fields.

※ Due to their low critical field
or depinning frequency

E.g. At QUAX
NbTi cavity



Performance comparable to Cu above 5 T


However, ReBCO (one of the HTS) is suitable since its upper critical field (H_{c2}) exceeds 100 tesla.

※ For more details, please refer to Dr. Danho Ahn's materials

HTS Cavities



- HTS cavity developed by the CAPP-HTS team

※ IBS-DMAG is the successor of IBS-CAPP



Commercially available 2D HTS tapes
→ Attach to the inside of the cavity

by soldering or gluing




The best-performing cavity
Frequency: 5.4 GHz
Q-factor: 13 M at 8 Tesla
(→ 100 times better than Cu cavity)

Goal: Integration of the Two Technologies

We are moving toward integrating HTS cavity technology with multiple-cell design for the next-generation axion experiment.



HTS cavity technology





Multiple-cell design

Development of an HTS double-cell cavity

The cavity design and copper components fabrication were carried out by Dr. Sungwoo and Dr. Sungjae.



- COMSOL simulation study

Alumina rod D3.5mm



Frequency: 4.17 – 4.44 GHz


Mass: 17.27 – 18.37 μg



Development of an HTS double-cell cavity

- Fabrication Process

1. HTS tapes are soldered onto copper components (endcap, sidewall, and partition)
2. Sidewalls are joined via laser welding & indium cold welding
3. 0.8 mm thick copper rings are tightly clamped around the sidewall and fixed in place using STYCAST 2850FT
4. The endcap is laser welded to both the sidewall and the partition.
5. Finally, they are electrically connected via indium cold welding.



Development of an HTS double-cell cavity

- Fabrication Process

1. HTS tapes are soldered onto copper components (endcap, sidewall, and partition)
2. Sidewalls are joined via laser welding & indium cold welding
3. 0.8 mm thick copper rings are tightly clamped around the sidewall and fixed in place using STYCAST 2850FT
4. The endcap is laser welded to both the sidewall and the partition.
5. Finally, they are electrically connected via indium cold welding.

Laser welding

Indium cold welding

STYCAST





→ Inside view of the sidewall

Development of an HTS double-cell cavity

- Fabrication Process

1. HTS tapes are soldered onto copper components (endcap, sidewall, and partition)
2. Sidewalls are joined via laser welding & indium cold welding
3. 0.8 mm thick copper rings are tightly clamped around the sidewall and fixed in place using STYCAST 2850FT
4. The endcap is laser welded to both the sidewall and the partition.
5. Finally, they are electrically connected via indium cold welding.





Indium cold welding

Performance Test

$$\frac{df}{dt} \propto Q_l$$

More than 3 times higher than that of a copper cavity

We achieved a Q-factor of $\sim 1.6 \times 10^5$ at a temperature near 10 K.



The next step is the magnet test.

Toward the Axion Search (Next Plans)

Alumina or Sapphire (high dielectric constant ϵ_r , low dissipation factor $\tan\delta$)

- Design and assembly of the tuning system, including a dielectric tuning rod → May
- Cryogenic performance tests with the tuning rod → May
- To perform an axion search in the frequency range 4.17 – 4.44 GHz (mass range 17.27 – 18.37 μeV), this cavity will be integrated into the **DMAG-12T** cryostat. → Starting in June



< **DMAG-12T** >

Refrigerator

- Model: LD400
- 10 mK (Base)
- 580 μW (100 mK)
- Dry type

Magnet

- 12 Tesla
- 96mm Bore
- Nb_3Sn
- Vendor: AMI

Summary

- The axion haloscope continues to be the most sensitive and promising method for detecting axion dark matter.
- IBS-DMAG succeeded IBS-CAPP and continues to carry forward the axion search.
- To accelerate the search, IBS-DMAG is integrating independently developed multiple-cell design and HTS cavity technology.
- The HTS double-cell cavity, excluding the tuning system, has been fabricated and demonstrated a Q-factor more than 3 times that of a copper double-cell cavity at cryogenic temperatures.
- This cavity is scheduled to be installed in DMAG-12T in June for the next phase of the axion search experiment.



IBS-DMAG
Creation Hall, KAIST Munji Campus

Thank you! 😊